

20x4 LCD display - I2C



Produktkode: 507

Tilgjengelighet: Opp til 1 mnd leveringstid

Pris: kr. 120,00

Short Description

Blue (Yellow)-Green-Serial-IIC-I2C-TWI-2004LCD-20X4-Character-LCD-Module-For-Arduino

Beskrivelse

Description:

Dedicated IIC control for Arduino, it only takes two IO

Adjustable contrast, the backlight control to provide library

Features:

High quality LCD screen, Yellow Green, clear display

IIC bus control, it only takes two IO ports

Backlight control, you can control via a jumper, you can also program control

Adjustable display contrast

5V power supply, the device address 0x27 (or 0x3F)

Compatible to Arduino

library

[Library for display](#)

SCL kobles til A4, SDA kobles til A5, Vcc til 5v Gnd til 0V

Eksempel på testskisse:

```
/**
 * Displays text sent over the serial port (e.g. from the Serial
 * Monitor) on
 * an attached LCD.
 */
#include
#include

// Set the LCD address to 0x27 for a 16 chars and 2 line display
LiquidCrystal_I2C lcd(0x27, 20, 4);

void setup()
{
  lcd.begin();
  lcd.backlight();

  // Initialize the serial port at a speed of 9600 baud
  Serial.begin(9600);
  lcd.setCursor(0,0); lcd.print("linje 1");
  lcd.setCursor(0,1); lcd.print("linje 2");
  lcd.setCursor(0,2); lcd.print("linje 3");
  lcd.setCursor(0,3); lcd.print("linje 4");
```

```

}

void loop()
{
// If characters arrived over the serial port...
if (Serial.available()) {
// Wait a bit for the entire message to arrive
delay(100);
// Clear the screen
lcd.clear();

// Write all characters received with the serial port to the LCD.
while (Serial.available() > 0) {
lcd.write(Serial.read());
}
}
}

```

Product Gallery

