

FPV transmitter 600mW

TS835**Produktkode:** 513**Tilgjengelighet:** Opp til 1 mnd leveringstid**Custom Field 5 (Location):** D16-18**Pris:** kr. 210,00

Short Description

TS835 5.8G 600mw 48CH 1A FPV Audio Video AV Mini Transmitter For RC Quadcopter

Beskrivelse

Specification:

Antenna connection: RP-SMA, jack (module side, both TX and RX)

Power:600mw

Channel:48CH

Frequency:5.8G

Video Format: NTSC/PAL

Antenna Gain: 2db

Working Current: 1A/5V

Output Impedance: 50 Ohm

Output Power: 13~14dBm

Operating Voltage: 7V~30V

Operating Temperature: -10~85?

Video Band Width: 0~8.0 MHz

Audio Carrier Frequency: 6.5 MHz

Video Input Level: 0.8~1.2 Vp-p

Video Input Impedance: 75 Ohm

Audio Input Level: 0.5~2.0 Vp-p
 Audio Input Impedance: 10K Ohm
 Dimension: 54mm x 32mm x 10mm
 Weight: 65g

Features:

- ?This is 48-channel transmitter of 5.8G 25mW A/V wireless system.
- ?48 channels: Cover A, B, C,D,H and L band (Air wave band).
- ?Digital phase-locked loop circuit, no channel drift issues.
- ?Small size, light weight, easy to carry
- ? Shape and power and is the same TS832,But it can enter 7-30V, with 5V 1A regulator function,also can give GoPro 3 SJ4000 and other power supply.TS832 without this feature (DJI Phantom 2 just need TS832)

Package Contents:

- 1 x TS835 Transmitter
- 1 x 5.8G Antenna
- 1 x Line

Frequency Range		CH					
		CH1	CH2	CH3	CH4	CH5	CH6
FR	FR1(A)	5865	5845	5825	5805	5785	5765
	FR2(B)	5733	5752	5771	5790	5809	5828
	FR3(C)	5705	5685	5665	5645	5885	5905
	FR4(D)	5740	5760	5780	5800	5820	5840
	FR5(H)	5658	5695	5732	5769	5806	5843
	FR6(L?)	5362	5399	5436	5473	5510	5547

Product Gallery

TS835



